



This 125 kHz OEM reader is a proximity reader designed to work with Passan Premium controllers. It is connected to the controller through 3 wires and manages a buzzer in addition to a bicolour led.

It has been especially designed to fit in a Urmet panel reference Elekta Steel.

Technical characteristics

- Windows dimensions : 42*42mm
- Plastic dimensions (l x w x d) : 80*50*27 (terminals included)
- Wiring : 3 wires 100m 6/10 (AWG24)
- Operating temperature : -20° to +60°
- Power supply: 12 Vcc /50mA (provided by the controller)
- Frequency : 125 kHz
- Reading range : Up to 4 cm (depending on the key)
- Protection : Diode and transil

Produits associés obligatoires


Accessoires



GB-010-012
CLE DE
PROXIMITE 125
KHZ GRISE



FD-010-169
TELECOMMANDE
HF 433MHZ - 4
TOUCHES



FD-010-070
LOT DE 10 CARTES
ISO 125 KHZ